P511 – Dual Fast Ethernet PMC

- **2 full-duplex or half-duplex channels**
- **10Base-T and 100Base-TX physical layer**
- **MAC layer realized in FPGA**
- **Local or external data buffer**
- **6 additional GPIOs**
- **Fully integrated to comply with IEEE802.3**
- **1500 VAC isolation voltage**
- **-40 to +85°C with qualified components**
- **32-bit/33-MHz PMC**
- **PMC based on USM concept**
- **Individual FPGA configuration**



The P511 is a 32bit/33MHz PMC with dual Ethernet functionality. The two channels can be accessed via two RJ45 connectors which are led to the front via an adapter cable from a SCSI connector. They support half duplex and full duplex operation.
The PMC offers the possibility to buffer all receive and transmit Ethernet frames either in a local or in an external data buffer. This makes it possible to provide a Worst Case Execution Time analysis which makes it particularly well suited for safety-critical applications.
Up to 6 GPIO lines can be used on the module for additional functionality.

The P511 is based on the USM concept. USM Universal Submodules make PMC modules more flexible than ever. The Ethernet functionality is realized via an IP core implemented inside its onboard FPGA. This function can be changed at any time through implementation of different IP cores. The corresponding line drivers are realized on the USM which is simply plugged on the P511. One alternative function is the combination of an Ethernet core with a fieldbus interface to build gateways.
The I/O mezzanine module is suitable for any PMC compliant host carrier board in any type of bus system, i.e. CPCI, VME or on any type of stand-alone SBC in telecommunication, industrial, medical, transportation or aerospace applications. It offers long-term availability for at least 10 years and is qualified for operation in the extended temperature range.

Diagram


Adapter cable to two RJ45 Connectors
50-pin front connector
Ethernet PHY Transceivers
GPIO Lines
FPGA
Ethernet MAC Layer
GPIO Controller
Memory Controller
DDR2 SDRAM 32 MB
PCI Interface
32-bit / 33-MHz

Technical Data

Ethernet Interface	■ Two 10/100Base-T Ethernet channels ■ Accessible on two RJ45 connectors via adapter cable ■ Half duplex/full duplex support
Memory	■ 32MB SDRAM memory □ Soldered □ DDR2 □ 132MHz memory bus frequency □ FPGA-controlled ■ 2MB non-volatile Flash □ For FPGA data and Nios® firmware □ FPGA-controlled
GPIO	■ Up to six lines controlled via software
FPGA	■ Standard factory FPGA configuration: □ Main bus interface □ Interrupt controller, SMBus controller □ 16Z087_ETH - Ethernet MAC IP core (2 IP cores for the 2 channels) □ 16Z043_SDRAM - SDRAM controller □ 16Z045_FLASH - Flash interface □ 16Z034_GPIO - GPIO controllers (2 IP cores, for onboard LEDs and 8-bit I/O) ■ The FPGA offers the possibility to add customized I/O functionality. See FPGA.
PMC Characteristics (PCI)	■ Compliant with PCI Specification 2.2 ■ 32-bit/33-MHz, 3.3V V(I/O) ■ Target and initiator
Peripheral Connections	■ Via front panel on a shielded 50-pin HP D-Sub SCSI 2 receptacle connector ■ Adapter cable to two RJ45 connectors included in the delivery
Electrical Specifications	■ Isolation voltage: □ 1500 VAC ■ Supply voltage/power consumption: □ +5V (-3%/+5%), 40mA □ +3.3V (-5%/+5%), 139mA
Mechanical Specifications	■ Dimensions: conforming to IEEE 1386.1 ■ Weight: 78g
Environmental Specifications	■ Temperature range (operation): □ -40..+85°C (qualified components) □ Airflow: min. 1.0m/s ■ Temperature range (storage): -40..+85°C ■ Relative humidity (operation): max. 95% non-condensing ■ Relative humidity (storage): max. 95% non-condensing ■ Altitude: -300m to + 3,000m ■ Shock: 15g/11ms ■ Bump: 10g/16ms ■ Vibration (sinusoidal): 1g/10..150Hz ■ Conformal coating on request
MTBF	■ 1 305 649 h @ 40°C according to IEC/TR 62380 (RDF 2000)
Safety	■ PCB manufactured with a flammability rating of 94V-0 by UL recognized manufacturers
EMC	■ Conforming to EN 55022 (radio disturbance), IEC1000-4-2 (ESD) and IEC1000-4-4 (burst)

Technical Data

Software Support	■ Windows® ■ Linux ■ QNX® ■ For more information on supported operating system versions and drivers see Downloads.

FPGA

This product offers the possibility to add customized I/O functionality in FPGA.

Flexible Configuration	■ Customized I/O functions can be added to the FPGA. ■ It depends on the board type, pin counts and number of logic elements which IP cores make sense and/or can be implemented. Please contact MEN for information on feasibility. ■ You can find more information on our web page "User I/O in FPGA"
FPGA Capabilities	■ FPGA Altera® Cyclone® II EP2C35 □ 33,216 logic elements □ 483,840 total RAM bits □ Supports Nios® II soft processor ■ Connection □ Functions can be linked to Wishbone or Avalon® bus □ Available pin count: 46 pins (FPGA to USM) □ Functions available via USM at front I/O connector ■ MEN offers a USM development kit and an FPGA Development Package as well as Flash update tools for different operating systems.

Configuration & Options

Standard Configurations

Article No.	Main FPGA Content	Soft Core	Memory	Signals	Cooling Method	Operation Temperature
15P511-00	2 Fast Ethernet Cores	No	32 MB RAM, 2 MB Flash	Front	Convection	-40..+85°C

Options

CPU	■ Nios® soft core implementation possible (e.g. for real-time Ethernet)
Rear I/O	■ Via Pn4 rear I/O connector
Cooling	■ Conduction Cooling

Please note that some of these options may only be available for large volumes. Please ask our sales staff for more information.

Ordering Information

Standard P511 Models	**15P511-00**	Dual Fast Ethernet, 2 Ethernet cores, 6 GPIO signals, front I/O, for convection cooled systems, -40..+85°C with qualified components
Miscellaneous Accessories	**05P000-01**	25 mounting screw sets to fix PMC/XMC modules on carrier boards
	05P511-00	P511 Ethernet HDSUB to 2 x RJ45 cable, -40..+85°C
Software: Linux	This product is designed to work under Linux. See below for all available separate software packages.	
	13MD05-90	MDIS5 System (and Device Driver) Package (MEN) for Linux. This software package includes most standard device drivers available from MEN.
Software: Windows®	This product is designed to work under Windows®. See below for all available separate software packages.	
	10Y000-78	Windows® Embedded Standard 7 BSP for F19P, F21P, F22P, F23P, G20, G22, CB70C, CB70, XM2, MM2, BC50M, BC50I, BL50W, BL50S, BC70M, BL70S, BL70W, BL70E, DC2, DC13, F205, F206, F210, F215, F216, G215, P506, P507 and P511
	13P511-77	Windows® Installset (MEN) for P511 (Includes all free drivers developed by MEN for the supported hardware.)
	13Z087-70	Windows® native driver (MEN) for 16Z087_ETH (Ethernet controller)
Software: QNX®	MENMON is MEN's firmware/BIOS for PowerPC® platforms.	
	13Z087-40	QNX® native driver (MEN) for 16Z087_ETH

For operating systems not mentioned here contact MEN sales.

Documentation	Compare Chart mezzanine functions on PMC/XMC and PC-MIP® » Download	
	20P511-00	P511 User Manual
	22Z087-ER	16Z087_ETH Errata

Contact Information

Germany

MEN Mikro Elektronik GmbH
Neuwieder Straße 3-7
90411 Nuremberg
Phone +49-911-99 33 5-0
Fax +49-911-99 33 5-901

info@men.de
www.men.de

France

MEN Mikro Elektronik SAS
18, rue René Cassin
ZA de la Châtelaine
74240 Gaillard
Phone +33 (0) 450-955-312
Fax +33 (0) 450-955-211

info@men-france.fr
www.men-france.fr

USA

MEN Micro Inc.
860 Penllyn Blue Bell Pike
Blue Bell, PA 19422
Phone (215) 542-9575
Fax (215) 542-9577

sales@menmicro.com
www.menmicro.com

The date of issue stated in this data sheet refers to the Technical Data only. Changes in ordering information given herein do not affect the date of issue. All brand or product names are trademarks or registered trademarks of their respective holders.
MEN is not responsible for the results of any actions taken on the basis of information in the publication, nor for any error in or omission from the publication.
MEN expressly disclaims all and any liability and responsibility to any person, whether a reader of the publication or not, in respect of anything, and of the consequences of anything, done or omitted to be done by any such person in reliance, whether wholly or partially, on the whole or any part of the contents of the publication.
The correct function of MEN products in mission-critical and life-critical applications is limited to the environmental specification given for each product in the technical user manual.The correct function of MEN products under extended environmental conditions is limited to the individual requirement specification and subsequent validation documents for each product for the applicable use case and has to be agreed upon in writing by MEN and the customer.Should the customer purchase or use MEN products for any unintended or unauthorized application, the customer shall indemnify and hold MEN and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim or personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that MEN was negligent regarding the design or manufacture of the part.
In no case is MEN liable for the correct function of the technical installation where MEN products are a part of.

Copyright © 2015 MEN Mikro Elektronik GmbH. All rights reserved.